



Speakers Timer



Dial button until desired time is set.

Press Button to start timer


Dots are flashing. Timer is running.



Press Button to pause timer.

Press Button to resume timer.

Time is over when last LED turns on. BAR starts to flash after 10% overtime (default setting).



Press Button to reset flashing bar

Timer can be reset any time by pressing Button 3 for seconds.




For Seconds timing, switch timebase to 't1'

For 5-Seconds timing, switch timebase to 't5'

For Minutes timing switch timebase to 'M' (default setting)

Messaging



Press Button when Display shows 'gC'.

Dial Button to select desired message.

Press Button to broadcast message.



To return to Timer setup, dial Button back to 'gC' and press.

Messages are moving light patterns, which can be broadcast to the speaker. Before a speech, the meaning of those patterns can be negotiated.

Examples:

- 1: speak faster
- 2: speak slower
- 3: come to the point
- 4: be more divergent
- 5: Audience has questions
- 6: change the subject
- 7: bad topic!
- 8: talk more about this
- 9: bravo!!!

Note:

Messaging can be use any time while Timer is running and will not affect speakers time. By default, both display types are selected to display message broadcast. If long and short displays are in use together, it may not be desired that the audience sees messages to the speaker. For this reason, Message Broadcast can be selected with either both, short desk Display only, long public Display only, or Controller only (for preview).


Message Broadcast Display select



While in messaging mode, dial Button to 'd' and press.

Dial the desired Display type and press. To return to messaging Mode, dial 'gC' again and press Button.


Extended Time



Dial Button until Display shows 'et' and press.

Dial Button to desired time extension.

Press Button to return to Timer setup.



While time is running, both dots flash at the same time, which indicates the extra time setting.

After regular speaking time is over, the LEDs of the Time-bar switch off from the back, until extended time is over.

Installation

